

ACCEPTED MANUSCRIPT

# Quench behavior of high temperature superconductor (RE)Ba<sub>2</sub>Cu<sub>3</sub>O<sub>x</sub> CORC cable

To cite this article before publication: Yawei Wang *et al* 2019 *J. Phys. D: Appl. Phys.* in press <https://doi.org/10.1088/1361-6463/ab1e2c>

## Manuscript version: Accepted Manuscript

Accepted Manuscript is “the version of the article accepted for publication including all changes made as a result of the peer review process, and which may also include the addition to the article by IOP Publishing of a header, an article ID, a cover sheet and/or an ‘Accepted Manuscript’ watermark, but excluding any other editing, typesetting or other changes made by IOP Publishing and/or its licensors”

This Accepted Manuscript is © 2019 IOP Publishing Ltd.

During the embargo period (the 12 month period from the publication of the Version of Record of this article), the Accepted Manuscript is fully protected by copyright and cannot be reused or reposted elsewhere.

As the Version of Record of this article is going to be / has been published on a subscription basis, this Accepted Manuscript is available for reuse under a CC BY-NC-ND 3.0 licence after the 12 month embargo period.

After the embargo period, everyone is permitted to use copy and redistribute this article for non-commercial purposes only, provided that they adhere to all the terms of the licence <https://creativecommons.org/licenses/by-nc-nd/3.0>

Although reasonable endeavours have been taken to obtain all necessary permissions from third parties to include their copyrighted content within this article, their full citation and copyright line may not be present in this Accepted Manuscript version. Before using any content from this article, please refer to the Version of Record on IOPscience once published for full citation and copyright details, as permissions will likely be required. All third party content is fully copyright protected, unless specifically stated otherwise in the figure caption in the Version of Record.

View the [article online](#) for updates and enhancements.

# Quench behavior of high temperature superconductor (RE)Ba<sub>2</sub>Cu<sub>3</sub>O<sub>x</sub> CORC cable

Yawei Wang<sup>1</sup>, Jinxing Zheng<sup>2</sup>, Zixuan Zhu<sup>1,3</sup>, Min Zhang<sup>1\*</sup>, Weijia Yuan<sup>1\*</sup>

<sup>1</sup>Department of Electronic and Electrical Engineering, University of Strathclyde, G1 1XQ, Glasgow, UK.

<sup>2</sup>Institute of Plasma Physics, Chinese Academy of Science, 230031, Anhui, P. R. of China.

<sup>3</sup>Department of Electronic and Electrical Engineering, University of Bath, BA27AY, Bath, UK

E-mail: [min.zhang@strath.ac.uk](mailto:min.zhang@strath.ac.uk); [weijia.yuan@strath.ac.uk](mailto:weijia.yuan@strath.ac.uk)

## Abstract

High temperature superconductor (HTS) (RE)Ba<sub>2</sub>Cu<sub>3</sub>O<sub>x</sub> (REBCO) conductor on round core cable (CORC) shows great advantages on high current capacity and power density. In REBCO CORC cables, current is redistributed among tapes through terminal contact resistances (TCR) when a local quench occurs. Therefore, its quench behaviour is different from single tape situation. To better understand the underlying physical process of local quenches in CORC cables, a new 3D multi-physics modelling tool for CORC cables is developed and presented in this paper. In this model, the REBCO tape is treated as a thin shell without thickness, and four models are coupled: *T*-formulation model, A-formulation model, a heat transfer model and an equivalent circuit model. The *T*-formulation is applied to the conductor shell only to calculate current distribution, which will be input into A-formulation model; the A-formulation is applied to the whole 3D domain to calculate magnetic field, which is then fed back to the *T*-formulation model. The hot spot induced quenches of CORC cables are analysed. The results show that the thermal stability of CORC cable can be considerably improved by reducing TCR. The minimum quench energy (MQE) increases rapidly with the reduction of TCR when the resistance is in a middle range, which is about  $5 \mu\Omega \leq R_t \leq 200 \mu\Omega$  in this study. When TCR is too low ( $R_t < 50 \mu\Omega$ ) or too high ( $R_t > 50 \mu\Omega$ ), the MQE shows no obvious variation with TRC. With low TCR, a hot spot in one tape may induce an over-current quench on other tapes. This will not happen in a cable with high TCR. In this case, the tape with hot spot will quench and burn out before inducing a quench on other tapes. The modelling tool developed can be used to design CORC cables with improved thermal stability.


Keywords: Quench behaviour, multi-physics modelling, HTS CORC cable, terminal contact resistance.

## 1. Introduction

The second generation (2G) high temperature superconductor (HTS), (RE)Ba<sub>2</sub>Cu<sub>3</sub>O<sub>x</sub> (REBCO) coated conductor, shows great potentials in many applications, owing to its high current density and high operational temperatures[1-3]. Some applications, like high field magnet and power transmission, require large current capacity[4-6]. Thus, three cabling concepts have been developed: Roebel cable[7-10], twisted stacked-tape cable[11, 12], and conductor on round core (CORC) cable[6, 13]. In CORC cables, the HTS tapes are wound helically on a round former, thus, the cable has great advantages on flexibility, mechanical strength, high current density & capacity, and AC loss reduction[13-17]. Tests have been performed on CORC cables in background fields up to 20 T, and a HTS magnet wound with CORC cables eventually reached a magnetic field of 20 T [18-21].

It has been reported that REBCO conductor may be damaged by temperature rise during a local quench [22-25]. Therefore, quench becomes one of the largest challenges for HTS applications. The quench behaviour of single 2G HTS tape has been studied by both experiments and simulations[26-30]. However, the quench behaviour of CORC cables is different from single HTS tapes. In CORC cables, HTS tapes are soldered to copper leads, the variation of terminal contact resistances often leads to an inhomogeneous current distribution among parallel tapes [31]. During a local quench, transport current will be redistributed among these parallel tapes through terminal contact resistances. Therefore, the quench behaviour of CORC cable is closely related to the terminal contact resistance. There are only few studies on 2G HTS CORC cable quenches [32], due to the difficulty of measuring current distribution within the cable. Therefore, a modelling tool is essential to help understand its quench behaviour under the influence of terminal contact resistance. So far, however, most of present modelling studies on HTS focuses on the electromagnetic behaviours [33-40]. There is no multi-physics quench modelling for 2G HTS CORC cables.

This paper presents a modelling study on the quench behaviour of HTS CORC cables. A novel multi-physics 3D quench model is developed using commercial finite element method (FEM) software. This model is based on the T-A formulation and is coupled with a heat transfer model and an equivalent circuit model in COMSOL Multiphysics. The current redistribution, temperature rise, normal zone propagation in the CORC cable are analysed during a hot-spot induced quench. The effect of terminal contact resistance on the local quench process is studied. The variation of minimum quench energy due to terminal contact resistance is discussed. This model enables the study of CORC quench behaviours to be practical, simple and extendable.



**Figure 1.** The geometry of the single-layer CORC cable consisting of three REBCO tapes.

**2. HTS cable model studied**

A HTS CORC cable sample is designed for the quench study in this paper, which is based on the cable model in references [41-43]. This cable has a single layer with three REBCO tapes, as shown in Figure 1. Winding angle of the cable is 40°. The ReBCO tape used here has a width of 4 mm and a thickness of 0.1 mm. The critical current of the tape is 100 A in self-field at 77 K. The operation temperature is 70 K, at which the tape’s critical current is about 148 A. The transport current of each tape is 120 A, so that a total current of 360 A is delivered by this cable. A heater is added on one tape to induce a local hot spot. The tape zone covered by this heater is 26.11 mm<sup>2</sup>. The tape with heater is labelled as Tape 1, and the other two tapes are labelled as Tape 2 and Tape 3 respectively, as shown in Figure 1. More specifications about this cable are shown in Table 1.


**Table 1.** Specification of the CORC cable model

Parameters		Quantity
Cable	Inner diameter	5.2 mm
	Winding angle	40°
	Pitch	19 mm
	Operating current	360 A
	Operating temperature	70 K
	Tapes per layer	3
REBCO tape	Width/Thickness	4 mm/0.1 mm
	Critical current, $I_c$ @ 77K/70K	100 A/ 148 A
	Critical temperature	92 K
	Operating current	120 A
	Substrate (Hastelloy)	50 $\mu m$
	Stabilizer (Copper)	2*20 $\mu m$

### 3. Numerical quench model

The 3D quench model consists of four modules, T-formulation model, A-formulation model, thermal model and equivalent circuit model, as shown in Figure 2. A thin shell assumption is applied to the coated conductor, thickness of the REBCO conductor is neglected, while its geometry structure along width and length direction remains the same, as shown in Figure 3. The T-formulation is applied to the conductor shell to calculate current distribution. The A-formulation is applied to the whole 3D domain to calculate magnetic field induced. The magnetic field obtained in A-formulation model is fed back to the T-formulation model, so that the electromagnetic coupling is achieved. The thermal model is applied to the conductor shell only, which is to calculate the temperature distribution. The heat source includes the external heat pulse and Joule heat generated by current. Temperature is fed back to the T-formulation model for the calculation of critical current. The equivalent circuit model is to calculate the current redistribution among tapes.

All these models are built and solved in COMSOL. The T-formulation model is solved in a PDE package, the A-formulation model is solved in Magnetic Field package, the thermal model is solved in a Heat Transfer on Shell package, and the circuit model is solved by an ordinary differential equation (ODE) package.



**Figure 2.** The numerical algorithm of the 3D quench model for CORC cables.

### 3.1. Thin shell approximation

The REBCO coated conductor is treated as a thin shell to effectively reduce the number of meshes as well as computation cost. It is reasonable to neglect the variation of magnetic field and temperature along the thickness direction, due to the high aspect ratio of REBCO conductor [33, 44]. However, current sharing occurs between superconducting layer and metallic stabilizer during quench operation, which has to be considered for the quench modelling.

As shown in Figure 3(a), the superconducting layer is covered by metallic layers (substrate and stabilizer). Transport current flows in the superconducting layers below critical current since the resistivity of the stabilizer layer is much higher than that of superconductor. The E-J relationship can be expressed as:

$$\mathbf{E}(\mathbf{J}) = E_0 \left( \frac{|\mathbf{J}|}{J_c(\mathbf{B}, T_h)} \right)^n \frac{\mathbf{J}}{J_c(\mathbf{B}, T_h)} \quad (1)$$

where  $E_0 = 1 \times 10^{-4}$  V/m,  $J_c$  is the critical current density, depending on the background field  $\mathbf{B}$  and temperature  $T_h$ . During a local quench, the resistance of the superconducting layer in normal zone increases dramatically, and some currents are forced out to flow into metallic layers. In this situation, the REBCO conductor is equivalent to two parallel resistances: the resistance of

superconducting layers  $R_{su}$  and that of the metallic layers  $R_m$ , as shown in the Figure 3(c) [45-48]. The governing equation of this equivalent circuit can be derived from Kirchhoff's law:

$$\begin{cases} E_0 \left( \frac{I_{su}}{I_c(B, T_h)} \right)^n - I_m \rho_m(T_h) = 0 \\ I = I_{su} + I_m \end{cases} \quad (2)$$

where  $I$  is the total current flowing in the REBCO conductor,  $I_{su}$  is the current flowing in superconducting layer, and  $I_m$  is the current flowing in metallic layers.  $\rho_m$  is the resistivity of the metallic layers, which is practically equal to the resistivity of the copper stabilizer [45]. It can be calculated using the following formula[45]:

$$\rho_m(T_h) = \rho_{copper}(300)[1 + 0.0039(T_h - 300)] \quad (3)$$

Therefore, the  $E$ - $J$  power law of REBCO conductor considering the overcurrent operation is revised as:

$$\begin{cases} E(J) = (J - J_{su}) / \sigma_m(T_h) \\ J = \frac{I}{S_c}; \quad J_{su} = \frac{I_{su}}{S_c}; \quad J_m = \frac{I_m}{S_c} \end{cases} \quad (4)$$

where  $S_c$  is the area of the conductor's cross section,  $J$  is the engineering current density flowing through the tape,  $J_{sc}$  and  $J_m$  are the equivalent current density flowing in superconducting layer and metallic layers respectively.


The dependence of the critical current on the temperature and external magnetic field can be expressed as[48-50]:

$$\mathbf{J}_c(\mathbf{B}, T_h) = \frac{I_{co}}{S_c} \cdot J_{cT}(T_h) \cdot J_{cB}(B_{par}, B_{per}) \quad (5)$$

$$J_{cT}(T_h) = \begin{cases} \left( \frac{T_c - T_h}{T_c - T_o} \right)^\beta & \text{if } T_h < T_c \\ 0 & \text{if } T_h \geq T_c \end{cases} \quad (6)$$

$$J_{cB}(B, \theta) = J_{cB}(B_{par}, B_{per}) = \frac{1}{[1 + \sqrt{(kB_{par})^2 + B_{per}^2} / B_c]^b} \quad (7)$$

where  $\beta = 1 \sim 2$  represents the temperature dependence of critical current,  $T_0 = 77$  K, and  $T_c = 92$  K is the critical temperature of REBCO conductor.  $B_{par}$  and  $B_{per}$  represent the magnetic fields parallel and perpendicular to the tape surface respectively, which will be obtained from the A-formulation model.  $k$ ,  $b$ ,  $B_c$  are shape parameters representing the field anisotropic characteristics of REBCO conductors, which are  $k = 0.0605$ ,  $b = 0.7580$ , and  $B_c = 103$  mT in this study.  $I_{co}$  is the critical current at 77 K in self-field, which is 100 A in the following study.



**Figure 3.** (a) Cross section of the REBCO conductor used in this study, which is from Superpower; (b) The approximated thin shell of the conductor; (c) the equivalent circuit model for the REBCO conductor.

### 3.2. *T*-formulation

The *T*-formulation model is applied to the REBCO conductor shell only. Based on the thin shell approximation, the current component normal to the tape surface is neglected, and the current only flows along the tangential direction of the tape surface. Therefore, a scalar variable *T* is defined to express the current density on this thin shell conductor[44, 51-53]:

$$\begin{cases} \mathbf{J} = \nabla \times (T\mathbf{n}) \\ \begin{bmatrix} J_x \\ J_y \\ J_z \end{bmatrix} = \begin{bmatrix} \frac{\partial(T \cdot n_z)}{\partial y} - \frac{\partial(T \cdot n_y)}{\partial z} \\ \frac{\partial(T \cdot n_x)}{\partial z} - \frac{\partial(T \cdot n_z)}{\partial x} \\ \frac{\partial(T \cdot n_y)}{\partial x} - \frac{\partial(T \cdot n_x)}{\partial y} \end{bmatrix} \end{cases} \quad (8)$$



where  $T$  is the normal component of the current vector potential  $\mathbf{T}$ , and it is applied to the REBCO conductor shell only.  $\mathbf{n}=[n_x, n_y, n_z]$  is the unit normal vector of the tape surface.


The governing equation of the model is derived from Faraday's law using variable  $T$ :

$$\nabla \times \mathbf{E}(\mathbf{J}) = -\frac{\partial \mathbf{B}}{\partial t} \quad (9)$$

where the magnetic flux density  $\mathbf{B}$  is obtained directly from the A-formulation model. Notice that the magnetic field  $\mathbf{B}$  here is not solved in the iteration of Equation (9), and it has no direct coupling with variable  $T$ . the left side of the Equation (9) can be obtained by inserting Equation (8) into Equation (1). Therefore, a vector problem with three variables in 3D space is reduced to a problem of the scalar variable  $T$  in a 2D thin shell, which significantly reduces the computation cost. A boundary condition is added on the edges of the conductor shell to impose the transport current[52, 54]:

$$T_1 - T_2 = \frac{I_k}{d}, \quad (k=1,2,3) \quad (10)$$

where  $d$  is the thickness of the REBCO conductor,  $T_1$  and  $T_2$  are the current vector potential on the two edges of the tape, as shown in Figure 4.  $I_k$  is the transport current of the  $k$ -th tape, which is calculated from the equivalent circuit model in section 2.4.



**Figure 4.** Domain relationship between the A-formulation model and  $T$ -formulation model.

### 3.3. $\mathbf{A}$ -formulation

To calculate the magnetic field, the  $\mathbf{A}$ -formulation model is applied to all domains including the shell conductor, as shown in the Figure 3. Here  $\mathbf{A}$  is the magnetic potential, defined as:

$$\mathbf{B} = \nabla \times \mathbf{A} \quad (11)$$


Coupling it to Ampere's law, the governing equation can be expressed as:

$$\nabla \times \nabla \times \mathbf{A} = \mu \mathbf{J} \quad (12)$$

A boundary condition (B.C.) is added on the thin shell conductor to impose the surface current,

$$\mathbf{n} \times (\mathbf{H}_1 - \mathbf{H}_2) = \mathbf{J} \quad (13)$$

where  $\mu$  is the permeability,  $\mathbf{H}_1$  and  $\mathbf{H}_2$  are the magnetic fields on both sides of the conductor shell. The current density  $\mathbf{J}$  is obtained from the  $T$ -formulation model and is applied to the REBCO conductor shell. The magnetic field  $\mathbf{B}$  obtained from this model will be fed back to the  $T$ -formulation model.



**Figure 5.** The equivalent heat capacity and thermal conductivity of REBCO conductor used in this study.

### 3.4. Heat transfer model

The heat transfer model is to calculate the temperature on REBCO conductors. Given the thin structure of the REBCO conductor and the high thermal conductivity of metallic stabilizer, the temperature difference perpendicular to the conductor surface is neglected, assuming the

conductor has a uniform temperature along the thickness direction. Therefore, the REBCO conductor is also approximated to a thin shell in this heat transfer model.

The governing equation of a typical heat transfer model in solid is as follows,

$$\rho C_p \frac{\partial T_h}{\partial t} + \nabla \cdot (-k \nabla T_h) = Q_s + Q_p \quad (14)$$

where  $C_p$ ,  $k$  are the heat capacity and thermal conductivity respectively, both of which are temperature dependent.  $\rho$  is the density.  $Q_s$  is the heat source power generated by the transport current in stabilizer;  $Q_p$  is the heat pulse power imposed, which induces a hot spot on the RBECO tape in the simulation. On the thin shell, the gradient operator  $\nabla T_h$  can be decomposed to a normal component  $\nabla_n T_h$  and a tangential component  $\nabla_t T_h$ .

$$\begin{cases} \nabla_n T_h = (\nabla T_h \cdot \mathbf{n})\mathbf{n} \\ \nabla_t T_h = \nabla T_h - (\nabla T_h \cdot \mathbf{n})\mathbf{n} \end{cases} \quad (15)$$

where  $\mathbf{n}$  is the unit normal vector of the shell. The equation (14) can be rewritten as:

$$\rho C_p \frac{\partial T_h}{\partial t} - k \nabla_n \cdot (\nabla_n T_h) - k \nabla_t \cdot (\nabla_t T_h) = Q_s + Q_p \quad (16)$$

Only the tangential component is considered in the thin shell. Therefore, the governing equation for the conductor shell is as follows [29]:

$$\rho C_p \frac{\partial T_h}{\partial t} - k \nabla_t \cdot (\nabla_t T_h) = \frac{Q_s + Q_p}{d} \quad (17)$$

$$\mathbf{n} \cdot (-k \nabla T_h) = h(T_h - T_e) \quad (18)$$

where  $d$  is the thickness of the REBCO conductor,  $T_e$  is the environment temperature, and  $h$  is the coefficient of heat transfer for the cooling. Eq. 18 is the cooling boundary condition, which is applied to the shell surface. Cooling on the edges of the conductor shell is neglected. In the study of this paper, an adiabatic boundary condition is applied to the tape, because the quench occurs in a very short time compared to time constant of thermal process. The heat transfer coefficient  $h$  is set to zero in this study.

Equivalent homogenous thermal conductivity  $k$  and heat capacity  $C_p$  are applied to the thin shell. They are calculated as parallel thermal resistances using following formula[46-48]:

$$k = \frac{k_1 S_1 + k_2 S_2}{S_1 + S_2} \quad (19)$$

$$C_p = \frac{C_{p1} m_1 + C_{p2} m_2}{m_1 + m_2} \quad (20)$$

where  $S_1$  and  $S_2$  are the cross section areas of substrate and stabilizer respectively,  $k_1$  and  $k_2$  are the thermal conductivity of substrate and stabilizer respectively,  $C_{p1}$  and  $C_{p2}$  are the thermal capacity of substrate and stabilizer respectively;  $m_1$  and  $m_2$  are the mass of the substrate and stabilizer respectively. These thermal parameters of substrate (Hastelloy) are from reference [55]; that of stabilizer (Copper) is from COMSOL material library. The equivalent thermal conductivity and capacity of REBCO tape used in this study are shown in Figure 5.

### 3.5. Equivalent circuit model and CORC cable sample


An equivalent circuit model is developed for this CORC cable to calculate the current redistribution among tapes during a local quench, as shown in Figure 6.  $R_{t,k}$  is the terminal soldering resistance of the  $k$ -th tape, which ranges from  $0.1 \mu\Omega$  to  $200 \mu\Omega$  in previous measurements [31]. The governing equation of this circuit model is as follows:

$$\begin{cases} u_k = I_k (R_{t,k} + R_{tape,k}) + \sum_{n=1}^3 \frac{dI_n}{dt} M_{k,n}; (k=1,2,3) \\ u_1 = u_2 = u_3 \\ I_{op} = I_1 + I_2 + I_3 \\ R_{tape,k} = \frac{R_{su,k} \cdot R_{m,k}}{R_{su,k} + R_{m,k}} \end{cases} \quad (21)$$

where  $u_k$  and  $I_k$  are the voltage and current of  $k$ -th tape respectively.  $I_k$  is fed back to the T-formulation model.  $I_{op}$  is the total current delivered by the cable.  $R_{tape,k}$  is the total resistance of the  $k$ -th REBCO tape;  $R_{su,k}$  is the resistance of superconducting layer, which is obtained from E-J power law in Equation (1);  $R_{m,k}$  is the resistance of stabilizer layer, which can be obtained from Equation (3).  $M_{k,n}$  is the mutual inductance between  $k$ -th tape and  $n$ -th tape, and it also represents

the self-inductance when  $k=n$ . Due to the symmetry of the three tapes in CORC structure, their mutual inductances and self-inductance  $M_{k,n}$  are the same. The current redistribution among three tapes in the same layer of a CORC cable mainly depends on the conductor resistance  $R_{tape}$  and terminal contact resistance  $R_t$ . Here the voltage on terminal contact resistance is called ‘contact voltage’  $u_{t,k}$ . The voltage of the tape does not include the terminal voltage, and it is called ‘tape voltage’  $u_{tape,k}$ .

Current redistribution to metallic cores (copper or stainless steel) is not considered in this study. Firstly, the pressed contact resistance between metallic cores and HTS tapes is much higher than the soldering terminal contact resistance. Experiments on ReBCO tapes have shown that no current is redistributed through pressed contact joints during a local quench. Secondly, in practical applications, the CORC cables often consist of dozens of HTS tapes, the total transport current is below 75% of  $I_c$  of the cable. If local quench happens on one tape, the other tapes can absorb all the redistributed current from the quenching tape, meanwhile still operate below critical current or slight overcurrent. Therefore, no current will be generated on the metallic core during a hot spot induced quench, since the resistivity of metallic core is much higher than that of superconductors. If major part of the tapes quenches simultaneously, there may be a current redistributed to metallic core.




**Figure 6.** The equivalent circuit model for the single-layer CORC cable with three REBCO tapes.

#### 4. Results and discussion

#### 4.1. Physical process of hot-spot induced quench

In this section, the hot spot induced local quench is studied using above model. The terminal contact resistances of all the tapes,  $R_t$ , are assumed to be uniform. The impact of non-uniform terminal contact resistances will be presented in future paper. The simulation process is as follows: firstly, the transport current of the CORC cable is ramped to 360 A, and the transport current of each tape is 120 A. Then, a heat pulse is imposed on Tape 1 to induce a hot spot. The period of the heat pulse is 100 ms and the heating power is constant during the heat pulse.

Figure 7 shows the depictions of the temperature and current density during a hot spot induced quench with heat pulse 144 mJ and terminal contact resistance  $100 \mu\Omega$ . In figure 7(c), the top temperature of the color legend for each temperature distribution is limited to  $T_c=92$  K to highlight the normal zone. The maximum temperature of the heating zone is pointed out by text. Figure 7(a) is the current flowing in superconducting layers. Figure 7(b) is the current flowing in metallic (copper) layers. The results show that some of the transport current in superconducting layer is forced out to copper layers when temperature rise is generated by heat pulse. Before that, all the transport current flows in superconducting layer below critical current. After the heater is turned off, current in copper layer continues generating heat. If the local heat accumulation is dissipated timely to other zones of the tape, the conductor will recover automatically from this heat pulse. In the case of Figure 7, the local heat accumulation is faster than the heat dissipation along the tape, temperature increase continuously and a quench is induced after heat pulse.




**Figure 7.** Distributions of current density in superconducting layer, current density in metallic layers and the temperature during a hot-spot induced quench, heat disturbance 183 mJ, terminal contact resistance  $100 \mu\Omega$ .

#### 4.2. Influence of terminal contact resistance

This section is to study the influence of terminal contact resistance  $R_t$  on the quench process of HTS CORC cables. The initial operating current is still 120 A for each tape, and the period of heat pulse is 100 ms. A series of simulations are conducted under different terminal contact resistances and heat pulses. The results show that the thermal stability of CORC cables is much higher than the single tape situation, because current of the tape with hot spot can be forced out to other tapes through the terminal contact resistance. Reducing the terminal contact resistance can significantly enhance the thermal stability of the cable. When the terminal contact resistance is high enough ( $R_t > 5 \mu\Omega$  in this study), the current redistribution mainly depends on the

terminal contact resistance. When the terminal contact resistance is low enough ( $R_t \leq 5 \mu\Omega$  in this study), the current redistribution will be limited by the critical current of tapes without hot spot.



**Figure 8.** Temperature of the hot spot under different terminal contact resistances, heat pulse 183 mJ.

Figure 8 shows the temperature of hot spot under different terminal contact resistances  $R_t$  when a heat pulse of 183 mJ is imposed. The temperature increases rapidly when the heat pulse is applied, and reaches to a peak value at the end of the heat pulse ( $t=100$  ms). A normal zone is induced by the hot spot and propagates to near zones. When the terminal resistance is low ( $R_t \leq 20 \mu\Omega$ ), the temperature of hot spot drops continuously after the heater is turned off, and finally the hot spot has a recovery from normal zone. Notice that when the terminal contact resistance is low enough ( $R_t \leq 5 \mu\Omega$ ), the temperature of hot spot shows no obvious difference under different resistances. When the terminal resistance is high ( $R_t \geq 50 \mu\Omega$ ), the temperature of hot spot shows a slight decrease after the heater is turned off, then increases continuously, and a quench is induced eventually.

To understand this result, we plot in Figure 9 the variation of the transport current and tape voltage in the process. Notice that the tape voltage  $u_{tape}$  doesn't include the voltage of terminal




contact resistance, it only includes the voltage of REBCO tapes. The results show that transport current is redistributed among tapes through terminal contact resistances when a hot spot is generated, due to the increases of tape voltage. The whole process can be divided into two stages: Stage I,  $t=0\sim 100$  ms, the heat pulse is applied; Stage II,  $t > 100$  ms, the heat pulse is turned off.

During stage I,  $t=0\sim 100$  ms, the current of Tape 1 with hot spot drops continuously due to the temperature rise of hot spot and normal zone propagation. The redistributed current is absorbed by other tapes. This current redistribution is mainly limited by two factors: terminal resistance and critical current. When the terminal resistance is low ( $R_t \leq 5 \mu\Omega$  in this study), the critical current seems to play a more important role. As shown in Figure 9( $a_1$ ) and ( $a_2$ ), from 0 ms to 28 ms, Tape 2&3 is below critical current 148 A, the tape resistance is nearly zero, so that a slight voltage rise can lead to a significant current redistribution. Thus, there is no significant voltage rise on the tapes. After  $t=28$  ms, Tape 2&3 flow over-current, and their tape voltages begin to increase rapidly. This voltage rise prevents further redistributed currents from Tape 1. Thus, current in Tape 1 drops much slower than that in previous period  $t < 28$  ms. At  $t=100$  ms, the temperature of hot spot rises to about 100 K, as shown in Figure 8, and a considerable normal zone is generated in Tape 1, as shown in Figure 10(b). However, the transport current of Tape 1 only decreases to 40 A, and Tape 2&3 flow an over-current 160 A, Tape 1 cannot force out more current to Tape 2&3.


The voltage of Tape 1 with hot spot is approximately the same with that of Tape 2&3 when the terminal contact resistance is low enough ( $R_t \leq 5 \mu\Omega$ ). As shown in Figure 9( $a_2$ ), at  $t=100$  ms, the tape voltages of Tape 1 and Tape 2&3 are about 6 mV, which are generated by normal zone in Tape 1 and over-current in Tape 2&3. Meanwhile, the currents of Tape 1 and Tape 2&3 are 40 A and 160 A respectively; the contact voltage of Tape 1 is  $4 \mu V$ , the contact voltage of Tape 2&3 is  $16 \mu V$ . The voltages of terminal contact resistances are negligible in comparison to the tape voltage of 6 mV. With the increase of terminal contact resistance, the contact voltage takes more and more proportion in comparison to the tape voltage. Obvious difference occurs on tape voltage when the terminal contact resistance is higher than  $5 \mu\Omega$ . Therefore, terminal voltage resistance plays a more important role on the current redistribution when the terminal contact resistance is high ( $R_t > 5 \mu\Omega$ ). With a terminal resistance of  $100 \mu\Omega$ , the tape voltage of Tape 1 is 12 mV at  $t=100$  ms, and the contact voltage of  $R_t$  is 6 mV at the same time. Thus, the

lowest current of Tape 1 is only about 60 A (at  $t=100$  ms), though a higher temperature is generated on hot spot and a larger normal zone is induced, as shown in Figure 10(b). High terminal resistance prevents current redistributing among tapes, which generates more heat and higher temperature. Therefore, higher terminal resistance leads to higher risk of quench.


During stage II,  $t > 100$  ms, the cable recovers from hot spot when the terminal contact resistance is low enough, which is  $R_t \leq 20 \mu\Omega$  in this study. The current and tape voltage of all tapes gradually recover to the initial state. The normal zone starts to shrink and finally disappears, as shown in Figure 10(a), since extra heat would be pulled out by cooling system in practical applications. When the terminal contact resistance is high ( $R_t > 50 \mu\Omega$ ), a quench is finally induced on Tape 1. The tape voltage increases fast with the normal zone propagation. The current of Tape 1 drops continuously, and the redistributed current leads to a continuous current increase on other tapes, as shown in Figure 9(c<sub>1</sub>). This over-current may finally lead to an over-current quench on Tape 2&3, if the protection system does not start timely.



**Figure 9.** Current and voltage of each tape under different terminal contact resistances; total transport current is 360 A, a heat pulse of 183 mJ is applied to Tape 1.



**Figure 10.** Normal zone propagation in the CORC cable when a heat pulse of 183 mJ is applied to Tape 1, total transport current is 360 A.



**Figure 11.** Dependence of minimum quench energy (MQE) on terminal contact resistance.

### 3.2. Minimum quench energy

The dependence of minimum quench energy (MQE) on terminal contact resistances has been shown in Figure 11. The result shows that the MQE drops rapidly with the increase of terminal contact resistance  $R_t$  when the resistance is between  $5 \mu\Omega$  and  $200 \mu\Omega$ . When the terminal


contact resistance is higher than  $100 \mu\Omega$ , the MQE reaches a minimum value. No further reduction of MQE is observed with further increase of the terminal contact resistance. When the terminal contact resistance is lower than  $0.5 \mu\Omega$ , no further increase of MQE is observed with the decrease of the terminal contact resistance.

Figure 12 shows the current and maximum temperature of each tape during three typical local quenches. With the same heat pulse 243 mJ, the current redistributions among tapes are almost the same when  $R_t = 0.1 \mu\Omega$  and  $R_t = 0.5 \mu\Omega$ , as shown in Figure 12( $a_1$ ) and ( $b_1$ ). The temperatures of the hot spot are similar, as shown in Figure 12( $a_2$ ) and ( $b_2$ ). When the terminal contact resistance is high, the current redistribution among tapes is very small. As shown in Figure 12( $c_1$ ), with  $R_t = 500 \mu\Omega$ , only 9 % of the transport current in Tape 1 is redistributed at the end of the heat pulse (when  $t=100$  ms). The MQE at  $R_t = 500 \mu\Omega$  is 87 mJ, while the MQE at  $R_t = \infty$  is 78 mJ. Therefore, when the terminal contact resistance is higher than  $500 \mu\Omega$ , the thermal stability of CORC cable with multiple REBCO tapes connected in parallel has no obvious improvement in comparison to that of single REBCO tapes.


Results in Figure 12 also show that, with a low terminal contact resistance, the hot spot of one tape may induce an over-current quench on other tapes. As shown in Figure 12(a) and (b), the current redistribution can lead to an over-current condition on the tapes without hotspot, accompanied by a heat accumulation and a temperature rise. When the temperatures of Tape 2&3 increase, tape resistances start to increase, and the currents are redistributed again, flowing back to tape 1. As shown in Figure 12 ( $a_1$ ) and ( $b_1$ ), the current of Tape 1 after  $t=3$  s increases rapidly to 120 A and all three tapes are quenched. With high terminal contact resistance  $R_t$ , tape 2&3 are less affected by the hot spot in Tape 1. As shown in Figure 12 ( $c_1$ ), although there is current redistribution to tape 2&3 from tape 1, there is no over-current quench on them. This is different from Figure 12 ( $a_1$ ) and ( $b_1$ ), where over-current quenches are generated in tape 2&3 due to current redistribution.

Overcurrent quench happens or not on all tapes is determined by the operating current, depending on whether the rest of the tapes can take the redistributed current. Figure 13 shows a simulation with a total applied current of 300 A, which is 100 A per tape. The current of Tape 1 drops to nearly zero, while currents flowing in other tapes are still below critical current.

Therefore, with low terminal contact resistances, it is impossible to induce a local quench on one tape when the other tapes can flow all the transport current below critical value.



**Figure 12.** Current of each tape, maximum temperature of all the tapes during a hot spot induced quench operation; transport current is 120A per tape, heat pulse  $Q_p$  is applied to Tape 1.



**Figure 13.** Current of each tape and maximum temperature of hot spot during a hot spot induced quench operation; transport current is 100A per tape, heat pulse  $Q_p$  is applied to Tape 1.

## 5. Conclusions

In this paper, a 3D multi-physics model is developed based on the T-A formulation to study the physical process of hot spot induced quench of REBCO CORC cables. The multi-physics model coupled four modules: T-formulation model on shell, A-formulation model, a heat transfer model on shell, and an equivalent circuit model. The electromagnetic and thermal processes are studied using this model, and the influence of the terminal contact resistance on the quench behaviour is analysed and discussed.

Current redistribution occurs among REBCO tapes of CORC cable when a hot spot is induced on one tape. Some currents of the tape with hot spot will be forced out to other tapes without hot spot through terminal contact resistance. The quench risk of CORC cable can be minimized effectively by reducing the terminal contact resistance. With low terminal contact resistances ( $R_t < 5 \mu\Omega$  in this study), the current redistribution mainly depends on the critical current of the tape without hot spot. With high terminal resistances ( $R_t > 5 \mu\Omega$  in this study), the current redistribution mainly depends on the resistance.

The MQE increases rapidly with the reduction of terminal contact resistance  $R_t$  when the resistance is in a middle range, which is between  $5 \mu\Omega$  and  $200 \mu\Omega$  in this study cases. When the terminal contact resistance is low enough ( $R_t < 5 \mu\Omega$  in this study), reducing the terminal contact resistance cannot further increase the MQE. When the terminal contact resistance is too high ( $R_t > 200 \mu\Omega$  in this study), the MQE drops to a ground value, which is similar to the MQE without terminal contacts. With a low terminal contact resistance, the hot spot of one tape may induce an overcurrent quench on the other tapes without hot spot. This will not happen in a cable with high terminal contact resistance. In this case, the tape with hot spot will quench and burn out before inducing another quench on other tapes.

The tape voltage and quench behaviour are significantly influenced by terminal contact resistances. Further work will be carried out in the future to develop quench detection and protection methods for CORC cables, as well as to experimentally validate the model proposed in this paper.

### Acknowledgments

This project was supported by EPSRC grant EP/P002277/1. The authors would like to thank Dr. Anna Kario (Karlsruhe Institute of Technology) for sharing useful information about the geometry and structure of CORC cables. Dr Min Zhang would like to thank the support of Royal Academy of Engineering Research Fellowship. Dr Yawei Wang would like to thank the support of European Union's Horizon 2020 research and innovation programme under the Marie Skłodowska-Curie grant agreement No 799902.

### References

- [1] Obradors X and Puig T 2014 Coated conductors for power applications: materials challenges *Superconductor Science & Technology* **27**
- [2] Zhao Y, Zhu J M, Jiang G Y, Chen C S, Wu W, Zhang Z W, Chen S K, Hong Y M, Hong Z Y, Jin Z J and Yamada Y 2019 Progress in fabrication of second generation high temperature superconducting tape at Shanghai Superconductor Technology *Superconductor Science and Technology* **32** 044004
- [3] Samoilenkov S, Molodyk A, Lee S, Petrykin V, Kalitka V, Martynova I, Makarevich A, Markelov A, Moyzykh M and Blednov A 2016 Customised 2G HTS wire for applications *Superconductor Science & Technology* **29**
- [4] Xiaorong W, Shlomo C, Daniel R D, William B G, Stephen A G, Hugh C H, Andy L, Soren O P, Danko van der L and Jeremy D W 2018 A viable dipole magnet concept with REBCO CORC ® wires and further development needs for high-field magnet applications *Superconductor Science and Technology* **31** 045007
- [5] Yuan W, Venuturumilli S, Zhang Z, Mavrocstanti Y and Zhang M 2018 Economic Feasibility Study of Using High-Temperature Superconducting Cables in U.K.'s Electrical Distribution Networks *IEEE Transactions on Applied Superconductivity* **28** 1-5
- [6] Laan D C v d, Weiss J D, Kim C H, Graber L and Pamidi S 2018 Development of CORC ® cables for helium gas cooled power transmission and fault current limiting applications *Superconductor Science and Technology* **31** 085011



- [7] Goldacker W, Frank A, Heller R, Schlachter S I, Ringsdorf B, Weiss K P, Schmidt C and Schuller S 2007 ROEBEL assembled coated conductors (RACC): Preparation, properties and progress *Ieee Transactions on Applied Superconductivity* **17** 3398-401
- [8] Long N J, Badcock R A, Hamilton K, Wright A, Jiang Z and Lakshmi L S 2010 Development of YBCO Roebel cables for high current transport and low AC loss applications *Journal of Physics: Conference Series* **234** 022021
- [9] Zermeno V M R, Grilli F and Sirois F 2013 A full 3D time-dependent electromagnetic model for Roebel cables *Superconductor Science & Technology* **26**
- [10] Jiang Z A, Staines M, Long N J, Badcock R A, Bumby C, Talantsev E, Hamilton K, Buckley R G and Amemiya N 2014 The scaling of transport AC losses in Roebel cables with varying strand parameters *Superconductor Science & Technology* **27**
- [11] Takayasu M, Chiesa L, Noyes P D and Minervini J V 2017 Investigation of HTS Twisted Stacked-Tape Cable (TSTC) Conductor for High-Field, High-Current Fusion Magnets *Ieee Transactions on Applied Superconductivity* **27**
- [12] Zhenan J, Naoyuki A, Kazuomi K, Yasuhiro I, Takashi S and Yuh S 2008 The dependence of AC loss characteristics on the space in stacked YBCO conductors *Superconductor Science and Technology* **21** 015020
- [13] Weiss J D, Mulder T, ten Kate H J and van der Laan D C 2017 Introduction of CORC (R) wires: highly flexible, round high-temperature superconducting wires for magnet and power transmission applications *Superconductor Science & Technology* **30**
- [14] Gömöry F, Šouc J, Vojenčiak M, Terzioğlu R and Frolek L 2017 Design and Testing of Coils Wound Using the Conductor-On-Round-Tube (CORT) Cable *IEEE Transactions on Applied Superconductivity* **27** 1-5
- [15] Sheng J, Vojenčiak M, Terzioğlu R, Frolek L and Gömöry F 2017 Numerical Study on Magnetization Characteristics of Superconducting Conductor on Round Core Cables *IEEE Transactions on Applied Superconductivity* **27** 1-5
- [16] Zhenan J, Naoyuki A, Naoki A and Kazuhiko H 2004 Total AC loss characteristics of untwisted and twisted Bi-2223 multifilamentary tapes and interaction between self and external magnetic fields *Superconductor Science and Technology* **17** 1311
- [17] Šouc J, Gömöry F, Kováč J, Nast R, Jung A, Vojenčiak M, Grilli F and Goldacker W 2013 Low AC loss cable produced from transposed striated CC tapes *Superconductor Science and Technology* **26** 075020
- [18] van der Laan D C, Goodrich L F, Noyes P, Trociewitz U P, Godeke A, Abrahimov D, Francis A and Larbalestier D C 2015 Engineering current density in excess of 200Amm(-2) at 20T in CORC (R) magnet cables containing RE-Ba2Cu3O7-delta tapes with 38 mu m thick substrates *Superconductor Science & Technology* **28**
- [19] Mulder T, Dudarev A, Mentink M, van der Laan D, Dhalhe M and ten Kate H 2016 Performance Test of an 8 kA @ 10-T 4.2-K REBCO-CORC Cable *Ieee Transactions on Applied Superconductivity* **26**
- [20] van der Laan D C, Weiss J D, Noyes P, Trociewitz U P, Godeke A, Abrahimov D and Larbalestier D C 2016 Record current density of 344Amm(-2) at 4.2K and 17T in CORC (R) accelerator magnet cables *Superconductor Science & Technology* **29**
- [21] Michael P C, Bromberg L, van der Laan D C, Noyes P and Weijers H W 2016 Behavior of a high-temperature superconducting conductor on a round core cable at current ramp rates as high as 67.8 kAs(-1) in background fields of up to 19T *Superconductor Science & Technology* **29**
- [22] Lindmayer M and Mosebach H 1997 Quenching of high-T-C-superconductors and current limitation - Numerical simulations and experiments *Ieee Transactions on Applied Superconductivity* **7** 1029-32
- [23] Wang X, Trociewitz U P and Schwartz J 2009 Self-field quench behaviour of YBa2Cu3O7-delta coated conductors with different stabilizers *Superconductor Science & Technology* **22**
- [24] Song H H, Gagnon K and Schwartz J 2010 Quench behavior of conduction-cooled YBa2Cu3O7-delta coated conductor pancake coils stabilized with brass or copper *Superconductor Science & Technology* **23** 10
- [25] Wang Y W, Zhang M, Yuan W J, Hong Z Y, Jin Z J and Song H H 2017 Non-uniform ramping losses and thermal optimization with turn-to-turn resistivity grading in a (RE) Ba2Cu3Ox magnet consisting of multiple no-insulation pancake coils *J Appl Phys* **122**
- [26] Liyang Y, Pei L, Tengming S and Justin S 2016 Quench degradation limit of multifilamentary Ag/Bi 2 Sr 2 CaCu 2 O x round wires *Superconductor Science and Technology* **29** 035010
- [27] Tengming S, Liyang Y and Pei L 2016 Feasible voltage-tap based quench detection in a Ag/Bi-2212 coil enabled by fast 3D normal zone propagation *Superconductor Science and Technology* **29** 08LT1
- [28] Wan Kan C and Schwartz J 2011 Three-dimensional Micrometer-scale Modeling of Quenching in High-aspect-ratio YBa 2Cu 3O 7-delta Coated Conductor Tapes - Part II: Influence of Geometric and Material Properties and Implications for Conductor Engineering and Magnet Design *IEEE Transactions on Applied Superconductivity* **21** 3628-34
- [29] Wan Kan C, Masson P J, Luongo C and Schwartz J 2010 Three-Dimensional Micrometer-Scale Modeling of Quenching in High-Aspect-Ratio Coated Conductor Tapes-Part I: Model Development and Validation *IEEE Transactions on Applied Superconductivity* **20** 2370-80
- [30] Song H and Schwartz J 2009 Stability and Quench Behavior of YBa2Cu3O7-x Coated Conductor at 4.2 K, Self-Field *Ieee Transactions on Applied Superconductivity* **19** 3735-43
- [31] Willering G P, van der Laan D C, Weijers H W, Noyes P D, Miller G E and Viouchkov Y 2015 Effect of variations in terminal contact resistances on the current distribution in high-temperature superconducting cables *Superconductor Science & Technology* **28**
- [32] Majoros M, Sumption M D, Collings E W and van der Laan D 2016 Stability and normal zone propagation in YBCO CORC cables *Superconductor Science & Technology* **29**
- [33] Amemiya N, Murasawa S-i, Banno N and Miyamoto K 1998 Numerical modelings of superconducting wires for AC loss calculations *Physica C: Superconductivity* **310** 16-29
- [34] Hong Z, Campbell A M and Coombs T A 2006 Numerical solution of critical state in superconductivity by finite element software *Superconductor Science & Technology* **19** 1246-52
- [35] Campbell A M 2009 A direct method for obtaining the critical state in two and three dimensions *Superconductor Science and Technology* **22** 034005
- [36] Gömöry F and Sheng J 2017 Two methods of AC loss calculation in numerical modelling of superconducting coils *Superconductor Science and Technology* **30** 064005
- [37] Zermeno V M R and Grilli F 2014 3D modeling and simulation of 2G HTS stacks and coils *Superconductor Science & Technology* **27**
- [38] Zhenan J, Naoyuki A and Masaaki N 2008 Numerical calculation of AC losses in multi-layer superconducting cables composed of coated conductors *Superconductor Science and Technology* **21** 025013

[39] Gao P F and Wang X Z 2018 Analysis of torsional deformation-induced degeneration of critical current of Bi-2223 HTS composite tapes *International Journal of Mechanical Sciences* **141** 401-7

[40] Peifeng G, Wan-Kan C, Xingzhe W and Justin S 2018 Mixed-dimensional modeling of delamination in rare earth-barium-copper-oxide coated conductors composed of laminated high-aspect-ratio thin films *Superconductor Science and Technology* **31** 074004

[41] Terzioğlu R, Vojenciak M, Sheng J, Gomory F, Ccedil;avus T F and Belenli I 2017 AC loss characteristics of CORC(RR)cable with a Cu former *Superconductor Science & Technology* **30**

[42] Vojenciak M, Kario A, Ringsdorf B, Nast R, van der Laan D C, Scheiter J, Jung A, Runtsch B, Gomory F and Goldacker W 2015 Magnetization ac loss reduction in HTS CORC (R) cables made of striated coated conductors *Superconductor Science & Technology* **28**

[43] Yawei W, Min Z, Francesco G, Zixuan Z and Weijia Y 2019 Study of the magnetization loss of CORC ® cables using a 3D T-A formulation *Superconductor Science and Technology* **32** 025003

[44] Amemiya N, Miyamoto K, Murasawa S-i, Mukai H and Ohmatsu K 1998 Finite element analysis of AC loss in non-twisted Bi-2223 tape carrying AC transport current and/or exposed to DC or AC external magnetic field *Physica C: Superconductivity* **310** 30-5

[45] Álvarez A, Suárez P, Pérez B and García L 2018 Coated Superconducting Tape Model Based on the Distribution of Currents Between the Tape Layers: Computing Implementation *IEEE Transactions on Applied Superconductivity* **28** 1-5

[46] Wan Kan C and Schwartz J 2012 A Hierarchical Three-dimensional Multiscale Electro-magneto-thermal Model of Quenching in REBa 2Cu 3O 7-delta Coated-Conductor-Based Coils *IEEE Transactions on Applied Superconductivity* **22** 4706010 (10 pp.)- (10 pp.)

[47] Sheng J, Chen Y, Lin B, Ying L, Jin Z and Hong Z 2014 Electrical-Thermal-Structural Coupled Finite Element Model of High Temperature Superconductor for Resistive Type Fault Current Limiters *Journal of Superconductivity and Novel Magnetism* **27** 1353-7

[48] Wang Y, Wan Kan C and Schwartz J 2016 Self-protection mechanisms in no-insulation (RE)Ba 2Cu 3O x high temperature superconductor pancake coils *Superconductor Science and Technology* **29** 045007 (11 pp.)- (11 pp.)

[49] Wang Y, Song H, Yuan W, Jin Z and Hong Z 2017 Ramping turn-to-turn loss and magnetization loss of a No-Insulation (RE) Ba2Cu3Ox high temperature superconductor pancake coil *J Appl Phys* **121**

[50] Grilli F, Sirois F, Zermeno V M R and Vojenciak M 2014 Self-Consistent Modeling of the I-c of HTS Devices: How Accurate do Models Really Need to Be? *Ieee Transactions on Applied Superconductivity* **24**

[51] Katsutoku T, Naoyuki A, Taketsune N, Osamu M and Takeshi O 2011 Model for electromagnetic field analysis of superconducting power transmission cable comprising spiraled coated conductors *Superconductor Science and Technology* **24** 085014

[52] Zhang H, Zhang M and Yuan W 2016 An efficient 3D finite element method model based on the T-A formulation for superconducting coated conductors *Superconductor Science and Technology* **30** 024005

[53] Zhu Z, Wang Y, Venuturumilli S, Sheng J, Zhang M and Yuan W 2018 Influence of Harmonic Current on Magnetization Loss of a Triaxial CORC REBCO Cable for Hybrid Electric Aircraft *IEEE Transactions on Applied Superconductivity* **28** 1-5

[54] Liang F, Venuturumilli S, Zhang H, Zhang M, Kvitkovic J, Pamidi S, Wang Y and Yuan W 2017 A finite element model for simulating second generation high temperature superconducting coils/stacks with large number of turns *J Appl Phys* **122** 043903

[55] Lu J, Choi E S and Zhou H D 2008 Physical properties of Hastelloy (R) C-276 (TM) at cryogenic temperatures *J Appl Phys* **103**